

Firmware Release Note



Model : ML-5010ND, 5012ND	Date :	February 11, 2016
---------------------------	--------	-------------------

Version	Category	Change Description
V2.00.02.34 (27-Mar, 2014)	Fix Defect	Change the warm-up speed to improve the noise of clutch.
V2.00.02.36 (28-Nov, 2014)	Add Func.	Add the error code(M3-1112, Jam Inside of Machine)
V2.00.02.49 (2-Mar, 2014)	Add Func.	Add Authentication Menu on SynThru Web Service
		XOA Web Version to be added to Configuration Report and SyncThru Web Service
		Support to install Application from Solution such as SyncThru6
		Support Top/Left margin at least -5~20mm
	Fix Defect	Enhancement of WLAN & WIFI_DIRECT
		[SWAS Job Accounting] Device didn't send a reponse to SyncThru Web Admin Service
		The machines connected in public network are being indexed by search engines like Google.
		Memory leakage when printing jpeg from SyncThru Web Service or usb memory
		Selected Secure options are not getting applied.
		SMTP is not working with "Port Number : 465" and "Connection with : SSL".
		Web Page is not displayed for User Access Control → Authentication
		"Unknown Error" is shown in device if paper jam occurs in MP tray
V2.00.02.51 (21-Sep, 2015)	Add Func.	Feature Support for SPDS Android App
		Apply the new font in PCL5, PCL6, PostScript
	Fix Defect	To avoid POODLE attack in OpenSSL V3 version
		Russia summer time issue
		Fixed value of "Network Connection Status" at Network ConfigurationReport Asia Hebron Time Zone is not getting Applied and Changed in DST
V2.00.02.53 (11-Feb, 2016)	Fix Defect	Fix the Motor lock error(A1-1110)


※ Note

- Please do not turn off the printer and your computer until firmware update finishes.
 - If you are using USB connection, disconnect all other USB printers from the PC.
 - The firmware update you are about to install has been tested for compatibility with Samsung toner cartridge products ONLY.
- Installing The upgrade may cause a non-Samsung toner cartridge to malfunction.
- Do not run your printer during the firmware update.(Do not have any print job)

How to update the firmware using a USB cable.

1. Make sure that the machine is connected to the PC with a USB cable.
2. Drag the firmware file(*.hd) and Drop down it on usblist2.exe.

And then, firmware update will be started automatically.



3. The firmware update will start.

Once the firmware update is complete, the machine will be rebooted automatically.

Updating from the Network

1. Go to the SyncThruWeb Service (SWS) main home page.

Login as Admin in SyncThruWeb Service.

NOTE: Login using the Administrator ID and Password established during initial machine setup.

2. Click [Maintenance] on the top menu.

And then click [Firmware Upgrade] or Application Management > Application

3. Click Add button
4. Click [Browse]. Choose installation file by browsing file system. And click OK button
5. The uploading step will start. After this step, next step will be started automatically.
6. The firmware update will start.
7. Once the f/w update is complete, the machine power-off and power-on automatically.