

Firmware Release Note



Model : ML-5510N, 5510ND, 5512ND, 6510ND, 6512ND	Date :	March 21, 2016
---	---------------	-----------------------

Version	Category	Change Description
V2.00.02.34 (27-Nov, 2014)	Add Func.	Add the error code (M3-1112, Jam Inside of Machine)
	Fix Defect	Few options are missing or added extra to the printed Menu map.
V2.00.60.38 (8-Dec, 2014)	Fix Defect	Control Panel Lock Feature is hanging when enable Control Panel Lock option
		Fix the network security issues
		Wireless key setting does not work properly if user input special char such as (<, >, &, ")
		Tray confirm message is disappeared after machine wakes up from power save
		in Network configuration report SMTP server is displayed as 0.0.0.0.25
		System crashes and reboots when PCI Wireless card is installed in the machine
		Fix the print quality problem
V2.00.60.48 (4-Mar, 2015)	Add Func.	Add Authentication Menu on SyncThru Web Service
	Fix Defect	[Job Accounting] Device didn't send a response to SyncThru Web Admin Service
		XOA Web Issues
V2.00.60.52 (21th-Mar, 2016)	Add Func.	Feature Support for SPDS Android App
	Fix Defect	Fix Russia summer time issue
		Fix the printing issue on Unix system (printer hang issue when test prn file is fired)
		Wrong permission is set for community name in SyncThru Web Service when it is Set through Fleet admin pro.
		Fix the Fuser Motor Failure error
		Fix PCL5 printing error (Image decoding error is occurred in specific size)


※ Note

- Please do not turn off the printer and your computer until firmware update finishes.
- If you are using USB connection, disconnect all other USB printers from the PC.
- The firmware update you are about to install has been tested for compatibility with Samsung toner cartridge products ONLY.
Installing The upgrade may cause a non-Samsung toner cartridge to malfunction.
- Do not run your printer during the firmware update. (Do not have any print job)

How to update the firmware using a USB cable.

1. Make sure that the machine is connected to the PC with a USB cable.
2. Drag the firmware file(*.hd) and Drop down it on usblast2.exe.

And then, firmware update will be started automatically.



3. The firmware update will start.

Once the firmware update is complete, the machine will be rebooted automatically.

Updating from the Network

1. Go to the SyncThruWeb Service (SWS) main home page.

Login as Admin in SyncThruWeb Service.

NOTE: Login using the Administrator ID and Password established during initial machine setup.

2. Click [Maintenance] on the top menu.

And then click [Firmware Upgrade] or Application Management > Application

3. Click Add button
4. Click [Browse]. Choose installation file by browsing file system. And click OK button
5. The uploading step will start. After this step, next step will be started automatically.
6. The firmware update will start.
7. Once the f/w update is complete, the machine power-off and power-on automatically.