

Firmware Release Note



Model : SCX-5835NX, 5935NX	Date :	2014-Dec-12
-----------------------------------	---------------	--------------------

Version	Category	Change Description
V2.00.03.07 (13-Jan, 2014)	Add Func.	Network PC Fax supports job accounting.
	Fix Defect	LDAP feature enhancement
	Add Func.	Add 20MB and unlimited to the Maximum size in previous case(1MB,2MB,3MB,4MB,5MB,10MB)
	Add Func.	Scan to SMB should work for MAC 10.7 (Lion OS)
	Fix Defect	Printer is rebooting when print now button is clicked on configuration report repeated 3 times.
	Fix Defect	Scan status in Scan to PC Application shows as Unknown, even if the device is connected.
	Fix Defect	SNMP Community Name Issue
V2.00.03.09 (24-Jul, 2014)	Fix Defect	Network Setting-100MB full should be configured , even network environment is 100M Half
	Fix Defect	Lock down to To/BCC/CC fields together (not separate lock feature)
	Fix Defect	Authentication returns back to default
	Fix Defect	SyncThru Web Admin Service LDAP login failed
	Fix Defect	Fax Modem Speed is not adjustable in the diagnostics(Service) Mode.
	Fix Defect	ScanToEmail is not working with 587 port


※ Note

- Please do not turn off the printer and your computer until firmware update finishes.
- If you are using USB connection, disconnect all other USB printers from the PC.
- The firmware update you are about to install has been tested for compatibility with Samsung toner cartridge products ONLY.
Installing The upgrade may cause a non-Samsung toner cartridge to malfunction.
- Do not run your printer during the firmware update.(Do not have any print job)

How to update the firmware using a USB cable.

1. Make sure that the machine is connected to the PC with a USB cable.
2. Drag the firmware file(*.hd) and Drop down it on usblist2.exe.

And then, firmware update will be started automatically.



3. The firmware update will start.

Once the firmware update is complete, the machine will be rebooted automatically.

Updating from the Network

1. Go to the SyncThruWeb Service (SWS) main home page.
Login as Admin in SyncThruWeb Service.
NOTE: Login using the Administrator ID and Password established during initial machine setup.
2. Click [Maintenance] on the top menu.
And then click [Firmware Upgrade] or Application Management > Application
3. Click Add button
4. Click [Browse]. Choose installation file by browsing file system. And click OK button
5. The uploading step will start. After this step, next step will be started automatically.
6. The firmware update will start.
7. Once the f/w update is complete, the machine power-off and power-on automatically.